

## OKY4092-5

**Product Name:0.28" DC 4-30V Digital Voltmeter Digital Amperemeter DC Voltmeter**

**Product Module:** OKY4092-5

### **Product Description:**

- 1.Power supply voltage: 4.5 ~ 30 V.
- 2.The test voltage: 0 ~ 100 V.
- 3.Below 10 V minimum resolution: 0.01 V.
- 4.More than 10 V minimum resolution: 0.1 V.
- 5.Test current range: 50A.
- 6.Testing current resolution:0.1A (Only can test forward current) .
- 7.Working current: < 20 mA.
- 8.Display usage: 0.28"LED ,red and blue.
- 9.External dimension: 48\*29\*21mm.
- 10.Mounting-hole Size :45.5\*26.5mm.
- 11.Measurement rate:  $\geq$  500 ms/time.
- 12.Accuracy: 1%( $\pm$  1 word).

### **Package Included**

Packing List	Qty
DC 4.5-30V Red&Blue Dual LED Digital Power Meter Voltmeter Ammeter	1